




LED A19 Motion Sensor

9W = 60W Incandescent

LED Motion Sensor lamps provide increased security and energy savings from only being lit when needed.



Product Description		LE-9A19/Motion Sensor
Body Size	L (mm)	112 ± 2
	D (mm)	60 ± 2
LED Source		Epistar
Dimmable		N
Motion Sensor		10' Range and radius; Turns on when motion is detected, and Turns off after 30 seconds of no movements being detected.
Input Voltage (V)		120V
Power (W)		9W
Luminous Flux		800LM
SDCM		<4
CRI		>80
Power Factor		>0.9
Life time (HRS)		10,000

Product Code	Description	CCT	Volts	Watts	Base	Lumens	Note
80178	LE-9A19 Motion Sensor	3000K	120V	9W	E26	800	
		4000K					
		5000K					

Disclaimer:

Subject to change without notice. Errors and omission excepted. Always make sure to use the most recent release.